42

CLAIMS

What is claimed is:

1. (Currently amended) A compound phase pattern for use on a reference surface of a
machine such as a magnetic recording device to compute the cross-track position relative to
said pattern, said pattern described in logical coordinates in the time or down-track direction
and in the orthogonal or cross-track direction, said pattern comprising a plurality of full servo
blocks, and said full servo blocks comprising:

   a. basic elements in the form of slender parallelograms with detectable transitions at
       their long edges, and

   b. certain of said basic elements called timing elements with said detectable transitions
       along isochrones or lines of equal values of said time coordinate, and

   c. one or more special groups of said timing elements to distinguish certain of said servo
       blocks or to identify a particular location as a timing reference within said servo
       blocks, and

   d. a plurality of phase bursts or groups of <u>said</u> basic elements at predetermined angles
       relative to said isochrones and with various predetermined pitches in said cross-track
       direction, and with the same period λ in said down-track direction and spanning
       predetermined numbers of cycles in said down-track direction, <u>with combinations of</u>
       <u>phases of said phase bursts encoded to define a unique cross-track position,</u>

   whereby both fine and coarse components of said cross-track position can be computed from
       phase information of data obtained from a transducer scanning said compound phase
       pattern only once in said down-track direction, and
   whereby the small variation of widths of said basic elements mitigates magnetic transfer of
       said pattern to said reference surface of said magnetic recording device, and
   whereby said compound phase pattern can be used as the final servo pattern for said magnetic
       recording device.

2. (Currently amended) Claim 1 wherein two of said phase bursts, designated burst A having
phase Φ_A and burst B having phase Φ_B <u>with said Φ_A and said Φ_B normalized to the standard</u>

RDWD0301-USA   App. No. 10/519,440 (Baker)   Amend. A   Claims   43 of 52

43

interval of values greater or equal zero and less than 2π, comprise said basic elements with the same cross-track pitch and with slopes of the same magnitude but of opposite sign in said logical coordinates, and wherein the fundamental phase difference or Φ_0 ~~can be~~is computed

35   from:

if $\Phi_A \geq \Phi_B$ then $\Phi_0 = \Phi_A - \Phi_B$ else $\Phi_0 = \Phi_A - \Phi_B + 2\pi$,

whereby said Φ_0 varies with said cross-track coordinate at twice the rate of Φ_A or Φ_B.

40   3.   (Currently amended) Claim 2 wherein said phase bursts other than said burst A or said burst B form an ordered sequence called higher order bursts, and each of said higher order bursts has said cross-track pitch equal to a predetermined integer multiplier times said cross-track pitch of said Φ_0 , and

45   ~~whereby~~wherein a predetermined constant or basic offset can be added to the measured phase of each of said higher order bursts and the result can be normalized to form its adjusted phase or principal value in the standard interval starting at 0 and including all positive values less than 2π , and with each of said principal values of said higher order bursts having value zero at the same cross-track location as a particular zero of said Φ_0.

50

4.   (Currently amended) Claim 3 wherein said integer multipliers of said higher order bursts are relatively prime, and said adjusted phase of each of said higher order bursts determines a unique segment index equal to the integer part of the product of said adjusted phase and said integer multiplier divided by 2π, and the unique cycle number of said ~~least significant~~
55   ~~phase~~Φ_0 can be computed from a predetermined algorithm based on said segment indices obtained for each of said higher order bursts, and said cross-track position coordinate can be computed as the sum of said unique cycle number plus the fraction given by said Φ_0 divided by 2π ,

44

60   whereby said cross-track position is unique over the number of cycles equal to the product of

said relatively prime integers describing said cross-track pitches of said higher order

bursts, and

whereby said cross-track position can be scaled to any convenient range.

65   5.   (Currently amended) Claim 3 wherein said cross-track pitch of the first of said ordered

sequence of said higher order bursts equals a first integer or burst-specific radix times said

cross-track pitch of said Φ_0 and said cross-track pitch of all other of said higher order bursts

equals a burst-specific radix times said cross-track pitch of the preceding member of said

ordered sequence of said higher order bursts,

70

whereby the integer part of the product of said adjusted phase of said higher order burst and

said burst-specific radix divided by 2π forms the segment index for said higher order

burst, and

whereby said segment indices can be combined with said radices in a positional number

75   system to identify a unique cycle number of said Φ_0, and

whereby the cross-track position coordinate can be computed as said unique cycle number

plus said Φ_0 divided by 2π, and

whereby said cross-track position can be scaled to any convenient range.

80   6.   (Previously presented) Claim 5 wherein said servo pattern further comprises a plurality of

short servo blocks that contain only a plurality of said phase bursts,

whereby the sample windows for said phase bursts of said short servo blocks are determined

by time delays measured from a preceding one of said servo blocks, and other values

85   of said phase information are taken from a preceding one of said servo blocks, and

whereby more of the reference surface is available for other uses.

7.   (Currently amended) A system for computing the absolute cross-track position of a read-

write transducer of a magnetic recording device comprising:

RDWD0301-USA   App. No. 10/519,440   (Baker)   Amend. A   Claims   45 of 52

45

90   a.   A compound phase pattern on a recording surface of said device defined by basic elements or slender parallelogram shaped regions with magnetization opposite the background state, said basic elements described in logical coordinates in the time or down-track direction and in the perpendicular or cross-track direction comprising:

      (i)   timing elements or certain of said basic elements with long edges or transitions

95   along isochrones or lines of equal values of said time coordinate, and

      (ii)   an ordered sequence of phase bursts comprising certain of said basic elements with long edges at ~~an a~~ predetermined angle relative to said timing elements, with the same predetermined pitch in the down-track direction, and with various burst-specific cross-track pitches;

100   b.   a first means to scan said pattern with said read-write transducer during relative motion in said down-track direction;

    c.   a second means to compute phase information from the signal generated by said transducer as it scans said phase bursts in said down-track direction;

    d.   a third means to combine said phase information from said phase bursts to compute a

105   unique cross-track position defined over a range determined by said pitches of said phase bursts;

       whereby said absolute cross-track position is computed from said phase information of a single scan of local data of said pattern, and

110   whereby the small variation of line widths mitigates magnetic transfer of said pattern to a recording medium, and

      whereby contemporary read-write channels can be used to analyze said phase information in said magnetic recording device.

115   8.   (Currently amended) Claim 7 wherein two of said phase bursts designated burst A and burst B comprise said basic elements with the same cross-track pitch and with slopes of the same magnitude but opposite signs in logical coordinates and said first means and said second means yield corresponding phase values Φ_A and Φ_B with said phase values in the standard interval $0 \leq \Phi < 2\pi$, and said third means combines said phase ~~information~~ values to

120   form the fundamental phase difference or Φ_0 according to:

46

if $\Phi_A \geq \Phi_B$ then $\Phi_0 = \Phi_A - \Phi_B$ else $\Phi_0 = \Phi_A - \Phi_B + 2\pi$,

whereby said Φ_0 varies in said cross-track direction at twice the rate of Φ_A.

9. (Previously presented) Claim 8 wherein said cross-track pitches of said phase bursts other

125 than said A and said B bursts are all integer multiples of half the pitch of said A or said B

burst.

10. (Currently amended) Claim 9 wherein said second means to compute phase information

adds a burst-specific constant offset to the measured value of said phase of each of said

130 higher order bursts and then normalizes the result to form its adjusted value in ~~the~~said

standard interval~~that starts at 0 and includes all positive values less than 2π, and~~ so that said

adjusted values of all of said higher order adjusted phases have a zero located at a particular

zero of said Φ_0.

135 11. (Currently amended) Claim 10 wherein ratios of said cross-track pitches of said higher

order bursts are all relatively prime integers times the cross-track pitch of said Φ_0 ,and said

third means forms <u>for each of said higher order bursts</u> the product of said relatively prime

integer with the ratio of said adjusted phase ~~over~~<u>divided by</u> 2π, and the integer part of said

product forms the segment index of said higher order burst, and said third means computes

140 the unique cycle number of said Φ_0 from a predetermined algorithm <u>based on said segment</u>

<u>indicies</u>, and said cross-track position coordinate is computed as the sum of said cycle

number plus the fraction of a cycle given by said Φ_0 divided by 2π ,

whereby said cross-track position coordinate can be scaled to any convenient range.

145

12. (Previously presented) Claim 10 wherein the ratio of said cross-track pitch of the first of

said ordered sequence of higher order bursts is an integral multiple or first burst-specific

radix times said cross-track pitch of Φ_0 , and said cross-track pitch of successive members of

said ordered sequence of higher order bursts is a burst-specific radix times said cross-track

150 pitch of the preceding of said higher order bursts, and said third means forms the product of

said burst-specific radix with the ratio of said adjusted phase over 2π, and the integer part of

47

said product forms the segment index of said higher order burst, and said third means

computes the unique cycle number of said Φ_0 as a positional number based upon said

segment indices and said radices, and said cross-track position coordinate is computed as the

155   sum of said cycle number plus the fraction given by said Φ_0 divided by 2π,

whereby said cross-track position coordinate can be scaled to any convenient range.

13. (Previously presented) A method of computing a cross-track position coordinate for a

160   system comprising steps:

a. providing a compound phase pattern defined in logical down-track and cross-track

coordinates on a scannable surface of said system, said pattern comprising extended

servo blocks comprising strips or regions in the form of slender parallelograms with

detectable edges wherein:

165   (i)   certain collections of said strips called timing elements have said detectable

edges at constant values of said down-track coordinate and certain of said timing

elements provide a timing reference and other groups of said timing elements

identify said extended servo blocks or identify a certain position within said

extended servo blocks, and

170   (ii)   a plurality of phase bursts each comprising phase elements or certain of said

strips spaced with the same period λ in said down-track direction and with said

phase elements of each of said phase bursts at the same predetermined angle

relative to said timing elements, said predetermined angle being unique for each

of said phase bursts;

175   b. providing transducer means to scan said compound phase pattern at essentially

constant relative speed in said down-track direction to produce a read signal from said

detectable edges;

c. providing signal processing means to measure the raw phases of portions of said read

signal from each of said phase bursts and to select the principal value in the standard

180   interval starting at **0** and including all positive values less than **2π**;

d. providing computation means to combine said phases and determine said cross-track

position;

48

    e. executing a self-test procedure to measure actual characteristics including minor alignment errors and eccentricity of said compound phase pattern;

185   f. recording results of said self-test procedure in a memory component of said system for use in later operation;

    g. operating said system with steps comprising:

        (i)   retrieving said results of said self-test procedure from said memory component

        (ii)   scanning said compound phase pattern with said transducer means to produce

190   said read signal

        (iii)   using said signal processing means to measure said phases of said phase bursts

        (iv)   applying said computation means to combine said phases and said results of said calibration procedure to determine said cross-track position

195   14. (Previously presented) The method of claim 13 wherein

    a. two of said phase bursts, designated burst A and burst B, have said phase elements with slopes of the same magnitude but of opposite sign in said logical coordinates, and

    b. all other of said phase bursts form an ordered sequence of higher order bursts wherein

200   the first higher order burst of said ordered sequence has said cross-track period that is an integer multiple or first radix times half of said cross-track period of burst A or burst B and wherein said cross-track period of other members of said ordered sequence of higher order bursts is equal to a burst-specific radix times the cross-track period of the preceding member of said ordered sequence of higher order bursts.

205

    15. (Currently amended) The method of claim 14 wherein during said operating step:

    a. the raw phase of each of said phase bursts is measured, and

    b. said results of said self-test procedure are used

        (i)   to add a standard offset to said raw phase of said B burst so that, on average,

210            $\Phi_B = \Phi_A$ at values of said cross-track coordinate where $\Phi_A = \pi/2$, and

        (ii)   to add a burst-specific offset to said raw phases of all said higher order phase bursts so the resulting phases have, on average, a zero at a particular cross-track location where $\Phi_B = \Phi_A$, and

49

(iii)   to compute the fundamental phase difference or Φ_0 as

215   **if $\Phi_A \geq \Phi_B$ then $\Phi_0 = \Phi_A - \Phi_B$ else $\Phi_0 = \Phi_A - \Phi_B + 2\pi$** ;

c. the resulting phase value of the first of said ordered sequence of higher order phase

bursts is adjusted by adding $(\pi - \Phi_0) / $ **(said first radix)**, and by adjusting said

resulting phase of other members of said ordered sequence of higher order bursts by

adding $(\pi - $ **said adjusted phase of the preceding higher order burst** $)$ over-said/

220   **(said burst-specific radix)** to urge said resulting phase value to the middle of the

appropriate phase segment, and normalizing said adjusted phase to the principal value

in the said standard interval starting at 0 and containing all positive values less than

2π, and

d. forming the result of multiplying said normalized phase value by said burst-specific

225   radix and dividing by 2π then selecting the integer part of said result as the segment

index for said phase burst, and

e. combining said segment indices and said first radix and said burst-specific radices in a

positional number system to provide the unique cycle index of the fundamental

phasesaid Φ_0 as the integer part and adding the fraction of said Φ_0 divided by 2π to

230   makeform said cross-track position coordinate.

16. (Previously presented) The method of claim 15 wherein small values of clock error τ are

computed from:

        $\delta = (\Phi_A + \Phi_B) / 2$

235   **if $\delta \geq \pi$ then $\tau = \delta - 3\pi / 2$ else $\tau = \delta - \pi / 2$** ,

and said clock error τ is subtracted from said resulting phase value of step (15. b.) before

normalizing

17. (Previously presented) The method of claim 15 wherein said predetermined angle of said

240 phase elements of one of said higher order bursts is zero, and said clock error τ is computed

as the variation of said phase from its average value, and said clock error τ is subtracted

from said resulting phase of step (15. b.) before normalizing.

50

18. (Previously presented) The method of claim 15 wherein said pattern further comprises
245   short servo blocks, said short servo blocks containing only certain of said position phase

bursts, and wherein sampling windows for reading said signal from said phase bursts of said

short servo blocks are determined by timing delays measured from a previous servo block,

whereby additional area of said scannable surface of said system is made available for other
250   uses.